



RED

RT-PG 5000/1 DD


Power Generator

Tank capacity 16 Litres



This "power station" supplies energy and provides security.

Power will be available whenever it is needed. Power failures or insufficient current supply are no longer a problem; whether during camping, at building sites, in homes or cottages, on boats or in the garden. This equipment can be used nearly everywhere, and, with its continuous power supply of 4,400 watts, provides sufficient power for many applications. The large 16-litres tank ensures continuous operation for twelve hours at 2/3 load. The power generator is powered by a high-quality diesel engine and is equipped with an overload switch. With this power generator you are optimally equipped, regardless if it should be powered with 12 V, 230 V or 400 V. The full power you can also drain from only one 230 V socket. With the economically diesel engine is the RT-PG 5000 DD a cheap alternative to petrol driven power generators.



12 V 230 V 230 V 400 V



Starter battery not included in delivery

Manufacturer	Type	V	Ah
Varta	53030	12 V	30 Ah
Bayern Batterien	53030	12 V	30 Ah
Exide	53030	12 V	30 Ah
Banner Batterien	53030	12 V	30 Ah

Features

- Economically diesel engine
- Large 16-litres tank for continuous power
- Over load switch for equipment reliability
- 2 x 230 V sockets for simple current drain
- 1 x 400 V socket for high power devices
- 1 x 12 V connection
- Changeover switch 230/400 volts
- Voltmeter
- Helpful tank level indicator
- Electric starter
- Decompression switch for problem-free starting
- Oil deficiency safety device to protect the motor
- High grade wheels, push handle and hook for easy transport
- Full crank shaft
- Automatic voltage regulation
- Starter battery not included in delivery



RED

RT-PG 5000/1 DD

Power Generator

Large 16-litres tank for continuous power

Helpful tank level indicator

Transport hook

Electric starter

Oil pilot lamp

Over load switch for 400 V socket

Decompression switch

Change-over switch 230/400 V

Voltmeter

Over load switch for 230 V socket


Over load switch for 12 V socket

1 x 400 V socket for high power devices


12 volts connection

2 x 230 V sockets for simple current drain

Push handle for easy transport



High grade wheels for easy transport



Logistic Information

Technical Data

Type:	RT-PG 5000/1 DD
Art.-No.:	41.523.56
Ident-No.:	01019
Bar code:	4006825 568288
Packing:	960 x 560 x 775 mm
Sales unit:	1 pc
20'':	180 pcs
40'':	364 pcs
40'' HC:	470 pcs
Net weight:	150.0 kg
Gross weight:	154.0 kg

■ Generator:	Synchronous
■ Continuous power (S1):	4,400 W an 400 V
or:	3,200 W an 230 V
■ Max. Power (S2 5 min):	5,000 W an 400 V
or:	3,500 W an 230 V
■ Voltage:	2 x 230 V 1 ~ / 1 x 400 V 3 ~
	1 x 12 V d.c.
■ Frequency:	50 Hz
■ Type:	Diesel engine
■ Cylinder capacity:	418 cm ³
■ Rotation speed motor:	3,000 rpm
■ Max. motor power:	7.36 kW / 10 HP
■ Fuel:	Diesel
■ Tank capacity:	16 l
■ Running time at 2/3 load:	approx. 12 hours
■ Noise level:	96 dB(A)

Abbildungen können nicht im Serien-Lieferumfang enthaltenes Zubehör darstellen / Illustrations can contain accessories, which are not included in standard extent of delivery. Abbildungen ähnlich, produktionsbedingte Abweichung vorbehalten / Illustration similar (in design), production-wise modifications reserved.
File: S:\shared-pool\Product-Dokumentation\T-Produktbeschreibung\30_n01\Originale_Englisch_PA04\4152356_01019.doc
Erstelldatum/create date: 10.03.2010 12:12:00Aktualisiert/up dated: 22.03.2010