



Einhell

BLUE

BT-BC 30 Battery charger

Art.-No. 10.781.00

Powerful and mobile workshop charger for 6 V / 12 V / 24 V charging voltage and jump start feature. Ideal for workshops and farmers. Charging capacity can be regulated with 6 settings. The jump start feature (100A/5s) can be activated with a remote cable (3 metre) by pressing a rocker switch. The large gauge show the current charging rate and the charging voltage. The insulated pole clamps warrant a perfect connection to battery poles. The unit is equipped with twice reverse voltage protection and overload protection. The housing ist made of scratch-resistant, powder coated sheet steel housing with a carrying handle.

Features

- Construction protection class I
- Sheet steel housing
- Carrying handle (1)
- Charging voltage switch (2)
- Charging rate switch (3)
- Voltmeter (4) and ammeter (5)
- Remote cable (3 m) with button (6)
- Overload- and reverse voltage protection
- Mains cable with mit safety plug
- Charging cable with insulated pole clamps (7)

Technical data

- Mains: 230 V ~ 50 Hz
- Charging capacity: 6 V = 0.7 – 21 A arithm. / 0.9 – 30 A eff.
12 V = 1.0 – 20 A arithm. / 1.6 – 30 A eff.
24 V = 1.8 – 14 A arithm. / 3.0 – 20 A eff.
- Jump start feature: 100 A (5 sec)
- For laed accus of min. 3 Ah up to max. 400 Ah
- Weight: 13 kg
- Packing dimensions: 425 x 330 x 225 mm
- Bar code: 4006825 101294
- Sales unit: 2 pcs



Abbildungen können nicht im Serien-Lieferumfang enthaltenes Zubehör darstellen / Illustrations can contain accessories, which are not included in standard extent of delivery. Abbildungen ähnlich, produktionsbedingte Abweichung vorbehalten / Illustration similar (in design), production-wise modifications reserved.

File: \\aa-fas-2\office\shared-pool\Product-Documentation\T-Produktbeschreibung\30_n0\Originale_Englisch_PA04\1078100_01037.doc

Erstelldatum/create date: 13.02.2008 09:28:00Aktualisiert/up dated: 08.01.2014