



RED

RT-PG 5500/1 D

Power Generator

Tank capacity 25 l

This "power station" supplies energy and provides security. Power will be available whenever it is needed. Power failures or insufficient current supply are no longer a problem; whether during camping, at building sites, in homes or cottages, on boats or in the garden. This equipment can be used nearly everywhere, and, with its maximum power supply of 5,500 watts, provides sufficient power for many applications. The large 25-litre metal tank ensures continuous operation for 9.5 hours at 2/3 load. The power generator is powered by a high-quality 4-stroke engine and is equipped with an overload switch. The automatic voltage regulation adjusts the motor power according to the decreased power and acquires the voltage to estimated standard again.



Power: max. 5500 W

Features

- Automatic voltage regulation
- Powerful 4-stroke drive motor
- Large 25-litre tank for continuous power with fuel gauge
- Oil deficiency safety device to protect the motor
- Overload switch for equipment reliability
- Changeover switch 230 / 400 V
- Ignition key switch with two keys
- Linkage to start the motor
- High grade wheels and folding handle for easy transport
- Stable base foot
- Full crank shaft





RED

RT-PG 5500/1 D

Power Generator



Logistic Information

Type:	RT-PG 5500/1 D
Art.-No.:	41.523.34
Ident-No.:	01019
Bar code:	4006825 568271
Packaging:	715 x 595 x 620 mm
Sales unit:	1 pc
20'':	81 pcs
40'':	180 pcs
40'' HC:	-- pcs
Net weight:	81.9 kg
Gross weight:	86.5 kg

Technical Data

■ Generator:	Synchronous
■ Max. Power:	5,500 W at 400 V socket
or:	3,300 W at 230 V sockets
■ Continuous Power:	3,600 W at 400 V socket
or:	3,000 W at 230 V sockets
■ Voltage:	2 x 230 V / 1 ~ / 1 x 400 V / 3 ~
■ Frequency:	50 Hz
■ Type:	1 cylinder, 4-stroke air-cooled
■ Cylinder capacity:	390 cm ³
■ Max. motor power:	9.55 kW / 13 HP
■ Fuel:	Petrol lead-free
■ Tank capacity:	25 l