



SE 3000 Power Generator

Art.-No. 41.524.01

This "power station" supplies energy and provides security.

Power will be available whenever it is needed. Power failures or insufficient current supply are no longer a problem; whether during camping, at building sites, in homes or cottages, on boats or in the garden. This equipment can be used nearly everywhere, and, with its maximum power of 2,800 watts provides sufficient power for many applications. The large 15-litre tank ensures continuous operation for 8 hours at 2/3 load. The power generator is powered by a high-quality 4-stroke engine and is equipped with an overload switch.

Features

- Large 15-litre tank for continuous power (1)
- Convenient fuel gauge (2)
- Reverse switch 230 / 400 V (3)
- 1 x 400 V socket (4)
- 1 x 230 V socket (5)
- Overload switch for equipment reliability (6)
- Practical voltmeter (8)
- Powerful 4-stroke drive motor (9)
- Linkage to start the motor (10)
- Oil deficiency safety device to protect the motor
- Full crank shaft
- Automatic voltage regulation
- Hinged push bracket (11) and wheels (7) for easy transport

Technical Data

- Generator: Synchronous
- Continuous Power (S1): 1 x 2,600 W / 400 V3~
1 x 1,500 W / 230 V~
- Max. Power (S2 2 min): 1 x 2,800 W / 400 V3~
1 x 1,800 W / 230 V~
- Nominal current: 1 x 230 V~
1 x 400 V3~
- Frequency: 50 Hz
- Type: 1 cylinder, 4-stroke air cooled
- Cylinder capacity: 207.7 cm³
- Max. motor power: 4.1 kW (5.5 HP)
- Fuel: Petrol
- Tank capacity: 15 l
- Running time at 2/3 load: approx. 8 hours
- Noise level: 96 dB (A)
- Product weight: 43.0 kg

Logistic Data

- Net weight: 43.0 kg
- Gross weight: 45.0 kg
- Packing dimensions: 635 x 500 x 483 mm
- Bar code: 4006825 565812
- Sales unit: 1 pc

