

## Power station EGS 2600

Art.-No.: **10.915.00**

bar code: 4006825105155

sales unit: 2 pcs

Practical, portable power supplies for 12 V DC (Direct Current). With a suitable connection cable the DC terminals of the EGS 2600 is ideal for connecting radio, TV, Laptops, Handy etc.

The power station provides also a boost device of 600 A / 5 sec. in cases of starting problems of motorcycles or cars.

A powerful compressor mounted in the rear produces compressed air up to 18 bar handy for inflating footballs and alike, little air mattresses etc.

A 3 watts light is integrated in the impact resistant housing provided with carrying handle.

### Features:

- Non spilling and leak-proof, maintenance-free lead power pack 12 V – 17 Ah
- 12 V terminal of the cigarette lighter socket for max. 10 A power draw
- Booster device 12 V – 600 A – (for 5 sec.)
- Lightning 12 V / 3 W (1)
- 18 bar integrated compressor with ON/OFF switch (2) and pressure gauge (3)
- Charging cables with fully insulated pole clips (4)
  - Battery charging control with indicator (5)
- ON/OFF lighting (6)
- ON/OFF charger clamps (7)
- Charging terminal for charger connection (8)
- Charger
- Connection cable with cigarette lighter adapter
- 3 pcs valve adapter set

### Technical data:

- Mains: 230 V ~ 50 Hz
- Rated Voltage at terminals: 12 V
- Rated current at terminals: 1000 mA
- Rated power at terminals: 12 VA
- Weight: 9.3 kg
- Packing Dimensions: 360x190x400 mm

