

Energy station EGS 1800

Art.-No.: **10.911.20**

bar code: 4006825105186

Sales unit: 4 pcs

Portable and handy power supplies for 3 V, 6V, 9V and 12V DIRECT CURRENT (DC) appliances. Due to varies DC exits it is ideal for connection of radios, TV sets, Laptops and mobile phones, etc. The integrated 180 Amps / 5 s boots device is a handy help in starting of a car or motorcycle. The housing is made of impact resistant plastics and equipped with carrying belt.

Accessories:

- Charging transformer (1)
- Connecting cable with cigarette lighter socket (2)

Features:

- Energy station: Sealed lead battery 12V – 11 Ah
- 3 V, 6 V and 9 V connection sockets Ø 6,3 mm (3) for a total of max. 1 Amps
- 12 V socket outlet from 2 cigarette lighter sockets (4) for max. 10 Amps.
- Boots device: 12V – 180A (for 5 s)
- charging cable with insulated pole clamps (5)
- Battery control indicator with 4 LED diodes (6)
- ON/OFF-LOADING-SWITCH (7)
- Charging sockets for charging and mains connection (8)
- Carrying belt (9)

Technical data transformer:

- Mains: 230V ~ 50Hz
- DC voltage at exit: 15V
- Current at exit: 500 mA
- Rated power at exit: 7,5 VA

