



SE 2100 Power Generator

Art.-No. 41.523.75

This "power station" supplies energy and provides security.

Power will be available whenever it is needed. Power failures or insufficient current supply are no longer a problem; whether during camping, at building sites, in homes or cottages, on boats or in the garden. This equipment can be used nearly everywhere, and, with its continuous power supply of 2,000 watts provides sufficient power for many applications. The large 15-litre tank ensures continuous operation for eleven hours at 2/3 load. The power generator is powered by a high-quality 4-stroke engine, is equipped with an overload switch and an automatic voltage regulation (AVR).

Features

- Large 15-litre tank for continuous power (1)
- Convenient fuel gauge (2)
- 2 x 230 V socket for simple current drain (3)
- Overload switch for equipment reliability (4)
- Practical voltmeter (5)
- Powerful 4-stroke drive motor (6)
- Linkage to start the motor (7)
- Oil deficiency safety device to protect the motor
- Full crank shaft
- Automatic voltage regulation

Technical Data

■ Generator:	Synchronous
■ Continuous Power (S1):	1 x 2,000 W
■ Max. Power (S2 5 min):	1 x 2,200 W
■ Nominal current:	2 x 230 V / 1 ~
■ Frequency:	50 Hz
■ Type:	1 cylinder, 4-stroke air cooled
■ Cylinder capacity:	196 cm ³
■ Max. motor power:	4.77 kW / 6.5 HP
■ Fuel:	Normal lead free
■ Tank capacity:	15 l
■ Running time at 2/3 load:	approx. 11 hours
■ Noise level:	95 dB (A)
■ Net weight:	38.5 kg
■ Gross weight:	41.2 kg
■ Packing dimensions:	635 x 445 x 480 mm
■ Bar code:	4006825 557091
■ Sales unit:	1 pc

